

4-23-2015

260513 - Medium Voltage Cable

Sandra Hickey
sandra.hickey@unh.edu

Follow this and additional works at: https://scholars.unh.edu/pdch_5_26

Recommended Citation

Hickey, Sandra, "260513 - Medium Voltage Cable" (2015). *Division 26 – Electrical*. 2.
https://scholars.unh.edu/pdch_5_26/2

This Article is brought to you for free and open access by the Chapter 5 – Technical Construction and Renovation Standards at University of New Hampshire Scholars' Repository. It has been accepted for inclusion in Division 26 – Electrical by an authorized administrator of University of New Hampshire Scholars' Repository. For more information, please contact nicole.hentz@unh.edu.

SECTION 26 0513 - MEDIUM VOLTAGE CABLE

PART 1 - GENERAL

- 1.1 The following Medium Voltage Cable components shall be submitted to UNH Facilities for approval:
 - A. Medium Voltage Underground Cable.
 - B. Medium Voltage Overhead Cable.
 - C. Low Voltage Cable below 600 volts.
 - D. Medium Voltage Terminations.

- 1.2 See Chapter 5, Division 01, Section 017700.1.1.B.1.i Closeout Procedures - Project Record Documents for equipment list requirements for all equipment provided in this section.

PART 2 - PRODUCTS

2.1 UNDERGROUND CABLE

- A. EPR Power Cable 35000 volts: Single Conductor, Shielded, 100% Insulation Level, AEIC-CS-6, MV-90 or MV-105 Sunlight Resistant, CT, USE.
- B. ERP Power Cable 5000/8000 volts: Single conductor, Shielded, 133% Insulation Level, AEIC-CS-6, MV-90 or MV-105 Sunlight Resistant, CT, USE.
- C. Cable Components for both 5000/8000 & 35000 volt cable (A & B).
 1. Conductor to be copper wire only.
 2. Shielding to be copper tape only.
 3. All medium voltage underground cable shall be installed in conduit encased in reinforced concrete with minimum 3" cover top, bottom and sides.
 4. All medium underground cable runs shall include a full size bare stranded neutral conductor, run with the ungrounded insulated phase conductors.
 5. The minimum allowable wire size for 5kV shall be #2 AWG Stranded Copper.
 6. The minimum allowable wire size for 35kV shall be 1/0 AWG Stranded Copper.

2.2 AERIAL MEDIUM VOLTAGE

- A. ACSR Type Cable.
- B. Hendrix Cable System.

2.3 AERIAL SECONDARY VOLTAGE

- A. ACSR Type Cable.
- B. Multiplex Type Cable.
 - 1. Duplex.
 - 2. Triplex.
 - 3. Quadruplex.

2.4 MEDIUM VOLTAGE TERMINATION

- A. Elastomeric Type shall be used.
- B. Single-Piece Terminators.
- C. Stress Cones.
- D. Splices.
- E. Loadbreak Elbows.
- F. Loadbreak Junctions.
- G. Cable Shield Adapters.
- H. Grounding Devices.

END OF SECTION 26 0513